

# Zeta Magnetic Door Holder & Bracket (ZT-DR240 & ZT-BR)



ZT-240



ZT-BR



## Description

The Zeta magnetic door holder is designed to retain a fire door open against the force of its own closing device. In the event of a fire, the door holder magnet can be turned off by the fire alarm, allowing the door to shut.

The manual release button is changeable from the base side to left or right. Cable entry is possible from rear side by means of enclosed exits from the base side, left or right.

An optional bracket is also available for floor or wall mounting (ZT-BR).

## Features

- ✓ Tested according to EN1155

## Specification

Model	ZT-DR240
Part No.	50-002
Rated Voltage	230V AC
Rated Current	6mA
Switch Through AUX	No
Needs Back EMF Diode	No
Holding Force	400 N
Dimensions (Main Unit)	110 x 85 x 38cm
Dimensions (Keeper Plate)	55 x 55 50mm
Weight (Main Unit)	404g
Weight (Keeper Plate)	153g